

12 Clintonville Road, Northford, CT 06472-1610  
Phone: 203-484-7161 Fax: 203-484-7118  
www.Farenhyt.com

## IDP-Minimon Monitor Module

### SPECIFICATIONS

|                                |                                                                                            |
|--------------------------------|--------------------------------------------------------------------------------------------|
| Nominal Operating Voltage:     | 15-32 VDC                                                                                  |
| Average Operating Current:     | 375µA Maximum (group poll); 350µA (direct poll); 600µA Maximum Communicating, IDC Shorted) |
| EOL Resistance:                | 47K Ohms                                                                                   |
| Maximum SLC Wiring Resistance: | 40 Ohms                                                                                    |
| Max. IDC Wiring Resistance:    | 1,500 Ohms                                                                                 |
| Maximum IDC Voltage:           | 11 Volts                                                                                   |
| Maximum IDC Current:           | 450µA                                                                                      |
| Temperature Range:             | 32°F to 120°F (0°C to 49°C)                                                                |
| Humidity:                      | 10% to 93% Non-condensing                                                                  |
| Dimensions:                    | 1.3" H x 2.75" W x 0.5" D                                                                  |
| Wire length:                   | 6" minimum                                                                                 |

### BEFORE INSTALLING

This information is included as a quick reference installation guide. Refer to the control panel installation manual for detailed system information. If the modules will be installed in an existing operational system, inform the operator and local authority that the system will be temporarily out of service. Disconnect power to the control panel before installing the modules.

NOTICE: This manual should be left with the owner/user of this equipment.


### GENERAL DESCRIPTION

The IDP-Minimon monitor module can be installed in a single gang junction box directly behind the monitored unit. Its small size and light weight allow it to be installed without rigid mounting (see Figure 1). The IDP-Minimon is intended for use in intelligent, two-wire systems where the individual address of each module is selected using rotary switches. It provides a Class B initiating device circuit for normally open contact fire alarm and security devices.

### COMPATIBILITY REQUIREMENTS

To ensure proper operation, this module shall be connected to a compatible Honeywell Farenhyt series system control panel (list available from Honeywell).

**FIGURE 1:**



C1063-00


### MOUNTING AND WIRING

NOTE: This module is intended to be wired and mounted without rigid connections inside a standard electrical box. All wiring must conform to applicable local codes, ordinances and regulations.

1. Connect the red (+) and black (-) wires to the positive and negative loop power leads of the signaling line circuit (SLC).
2. Connect the violet (+) and yellow (-) wires to a two-wire, normally open initiating loop.
3. Install the specified EOL resistor value to terminate the initiating loop.
4. Set the address on the module per job drawings.
5. Install the module in the desired mounting location.

NOTE: All references to power limited represent "Power Limited (Class 2)".

**FIGURE 2. TYPICAL CLASS B STYLE B INITIATING DEVICE CIRCUIT CONFIGURATION:**



C0614-02